

# User Manual for Tuya Smart V3.18.1



### tuyo<sup>®</sup>涂鸦智能

# Index

1. App Download	-3
2、Register/Log in/Forgot Password	4
3、Use App	9
3.1 Home/Members Management	-10
3.2 Voice Assistant	-15
3.3 Environment Information	-18
3.4 Add Devices	-19
3.4.1 Add Manually-Wi-Fi Device-EZ Mode	-21
Add Manually-Wi-Fi Device-AP Mode	-22
Add Manually-Wi-Fi Device-Enter Wi-Fi Password	-23
Add Manually-Wi-Fi Device-Network Configuration	-24
Add Manually-Wi-fi bluetooth dual mode network	-28
3.4.2 Add Manually-Zigbee Device	-35
3.4.3 Add Manually-IPC Device-Wired Network Configuration	-38
3.4.4 Search Device	-40
Search Device-Request for Permission	-41
Search Device-EZ mode that Supports Add Devices Manually	-43
3.4.5 can to Pair Devices : Scan QR code in NB Products or Enter Code	-44
Added the distribution method of scanning code	
distribution network	-45
3.5 Device List	-46
3.5.1 Device management	-47
Room Sequence	48
3.5.2 Device/Room List	49
3.5.3 Quick Actions for Common Functions	50

#### 4、 Device Contro

4.1 Device Control **Device** Control **Device** Contro 4.2 Device Contro 5, Smart-Automa 5.1 Smart-Auton Smart-Autom Smart-Autom Smart-Autom Smart-Autom 5.2 Smart-Scenar Smart-Scene and recovery 5.3 Smart-Add/Ed Smart-Scene 5.4 Smart-Scenar 6、My Home-----7、Me″ -----7.1 "Me" -Watc 7.2 "Me" -App 7.3 "Me" -Mess 7.4 "Me" -FAQ 7.5 "Me" - More 7.6 "Me" -Abou 8、Personal Cent 8.1 Account & See 8.2 Personal Cen



)	53
ol-Individual Control	-54
ol-Device Management	-55
ol-Device Sharing	-56
ol-Group Control	-57
ation	59
nation-Add Condition	-66
ation-Add Task	-67
ation-Effective Period	-68
ation-Examples	-69
ation-Push messages support	
multiple selection	-70
10	-71
-Zigbee gateway linkage data back	up
/	-/3
alt/Delete	-/5
OGS	-/ð 70
IO Execuation in LAIN	-/9
	80
	81
	-82
Notification Settings	-83
Sege Center	-80
	-89
'Services	-90
11	- 72
curity Account Deactivation	95
tor Dettorn Lock	-94 05——
	-90



#### **Download App NO.1**

You can download the App by searching "Tuya Smart" in mobile app stores or scanning the following QR code.





#### tuyo<sup>®</sup>涂鸦智能

# **NO.2** Register/Log in/Forgot Password



# Register 1.Click "Sign Policy after it and enter the



- 1.Click "Sign Up" and read the Privacy Policy after it pops up. Click "Agree"
- and enter the registeration page.

#### tuyon涂鸦智能

#### **Register/Log in/Forgot Password NO.2**

19:14 7	<b></b>	10:49		<b>?</b> •,	10:49	···· 🗢 🔳,
<		<			<	
Register		Enter Ver	ification C	ode	Set Password	
China	>					
Mobile Number/Email					Password contains 6 to 20 characters letters and digits	, including
		Verification code phone: 86-13809	has been sent to yo 1334456, Resend (5	ur mobile 8s)		
I Agree User Agreement and Privacy Potential	blicy					
	- r	1	2	3		
	-			DEF		
		4 сні	5 JKL	б		
		7 PQRS	8 TUV	9 wxyz		
			0	$\langle \times \rangle$		
		-		•		

"Done".



- 2.You can use email or mobile number
- as your account to register. The
- country/region of the APP will be the
- same as the phone's. You can also
- change it by yourself when
- registering. (You cannot change the
- country/region after the
- registeration). Enter mobile
- number/email and click" Get
- Verification Code";
- 3.Enter the verification code and turn
- to the password setting page. Set
- your password as required and click

#### tuya。涂鸦智能

#### **Register/Log in/Forgot Password NO.2**

17:06 -7 🗢 💽	
<	
Log In	
China >	
Please enter your account	
Password	
Forgot Password	
0 8 0	
Login means that you agree with <u>User</u> <u>Agreement</u> and <u>Privacy Policy</u>	

#### Log in

If you already have an account, choose "Register with Existing Account" and enter the log in page. 1. The system will automatically locate the current country/region you are in. Or you can choose the country/region by yourself. 2.Enter mobile number/ email and password. Thirdy-party Social Account Log in If you have downloaded Wechat or QQ on your phone, you can click the Wechat/QQ icon in the log in page. You can log in using your wechat/QQ account after authorizing it.If you are

using iPhone, you can also log in with Apple ID.





#### **NO.2 Register/Log in/Forgot Password**

17:06 🕫	🗢 💽	4:52	🗢 🗩
<		<	
Log In		Forgot Password	
China	>	China +86	>
Please enter your account		Mobile Number/Email	
Password			
Log In Forge	ot Password		

# **Forgot Password**

- If you forget your password, you can
- follow the procedures and retreive it.
- 1. Click "Forgot Password";
- 2. The system will automatically locate
- the current country/region you are in.
- You can also choose the country/region by yourself.
- 3. Enter the mobile number/email that
- you use to register and click "Get
- Verification Code".





# **NO.2** Register/Log in/Forgot Password



SMS or email; password. automatically.)



- 4. Enter the verification code you receive in SMS or email;
- 5. Enter your new password, click "Done" to
- reset the password. The app will
- automatically log in using your new
- 6. For security concerns, the APP will detect risks in the phone system when logging in. If it detects root or jailbreaking risk, it will pop up "Security Reminder" and you can choose whether to exit the app or not. (If you do not choose anything, the app will exit automatically.)

#### tuyo<sup>®</sup>涂鸦智能

# **NO.2** Register/Log in/Forgot Password





#### **Experience Mode**

1. Click "Try now", a prompt page will appear.

2. In Experience mode, the following

functions are not be supported: Cloud

storage, Third-party voice control, and Device sharing.

3. Click "Continue" to accept the experience mode notices, and you will enter the home page.



10:53	···· 🗢 🔳 )	5:00	<b>?</b> •	5:08 🕇		<b>?</b> 🗩
	0 🕂		Ξ	<	Home Management	
		Tap to Set Nicknam	e ,	Tuya		>
				Tuya		>
		Arrow Management		Add new		
No devices, please	add	💬 Message Center	• >			
Add Device		FAQ & Feedback	>			
		More Services	>			
		Settings	>			
Home Smart	Me	Home Smart	•			



When new users enter the app,
 they will see the home page where
 the devices are listed. The user profile
 will be shown in the top left corner.
 There will be room and environment
 information before you complete the
 home information.

2. Click "Me" in the lower right
corner and choose "Home
Management" to enter the page.
3. If you are a new user, when you
click "Home Management", the app
will directly turn to the page where
you can add new homes and edit
home information.

4. If you have already added homes before, you can click "Add new" to enter the page.



# **NO.3.1** Home/Member Management



5.You ca like. (29 6. "Hot phone l location "Confit correct.



- 5.You can change the "Home Name" as you like. (25 characters maximum) ;
- 6. "Home Location" will change with yourphone location. You can also change the homelocation by setting the home coordinate. Click
  - "Confirm" after making sure the location is orrect.

#### tuyaầ涂鸦智能

# **NO.3.1 Home/Member Management**

10:53		🗢 🗩,	10:57		🗢 🗩	10:57		
Cancel Ec	dit Home Info	Save	Cancel	Add Room	Save	Tuya 🗸		Û
Home Name* E	inter		Room Name	9			Sunny	
Home Location	Set	>	Recommend			9.0 °C Outdoor Temperat	Comfortab ure Outdoor Humid	ity Outdoor
Rooms:			Living Roor	m Master Bedroom	)	All Devices	Living Room	Master Bedro
Living Room		<b>S</b>	Second Bed	Iroom Dining Room Study Room Porce	ch	-		
Master Bedroom		0	Balcony	Kids Room Close	et			
Second Bedroom		0						
Dining Room		<b></b>					$\left( + \right)$	
Kitchen		<b>S</b>					No devices, pleas	e add
Study Room		<b>S</b>					Add Device	
Add Room								



-Ò.

Smart

Home





7. You can choose the room name given by the system. Or click "Add Room" to customize the room names (25 characters maximum). 8. After you complete the home information and turn to the home page, you will see information such as weather, humidity level and room names. If you have added more than one homes, click the button on the upper left to switch and manage other homes.



# **NO.3.1** Home/Member Management



9. In "Home" page, you can click the button in the upper left to switch to other homes.

10. In "Home Management", you can edit the existing homes and add new homes. An account can control multiple homes, and the smart devices in different homes will not interefere with each other when using.





#### NO.3.1 Home/Member Management

5:33 <b>1</b>		🗢 🔳,
🗸 Tuya		
Tuya		
🔶 Home	Management	
All Devices	Living Room	Master Bedroo ····
	+	
	No devices, pleas	se add
	Add Device	
Home	-Ŏ- Smart	Me

After the invitation is sent, it will show "waiting to join " before the user agree to join.

Administrators can click here to invite other people to join this home.

11:21			,
<	Home	e Settings	
Home N	ame	Tuya	>
Room M	anagement	6 Room(s)	*
Home Lo	ocation Han	gzhou Wuchanggang Road	>
Home Me	mbers		
	<b>Tuyaer</b> 86-135138426	Home owner	>_
	Tuyaer Waiting to join.	Administrator	>
	Tuyaer 316063723@q	iq.com	>
Add Me	mber		
Transfer	Home Owne	ership	>
	Delet	te family	

smarts.



#### **11. Click "Tuya" to enter Home Settings** page, as shown in the pictures

- Edit the rooms in homes and manage the deivces in the rooms.
- Home owner has the highest access. It can manage all the devices, rooms, smarts, administrators and members in the home.
- Administrator can manage devices, rooms, smarts and members.
- Member can only use devices and



#### NO.3.1 **Home/Member Management**

3:29			<b>?</b>	4:03					
<	Home Ma	nagement		<	Alarm	Home	Bulletir		⊚
Тиуа			>	19 Noven	nber				
Tuya Waitin	g to join		>	ណ៍	Add Fam 樱桃 has a all devices family.	<b>ily Membe</b> dded you to and smart	er o "Tuya". Yo scenarios o	3:29:51 F ou can us f the	PM e
Add new									
<b>Confirm Invitation</b> You are invited to join the family "Tuya" to enjoy a smart life. Do you want to join the family?			0	(	Click here	or pull up	to load m	ore	
De	cline	Accept						道	
					_				

messege center.



12. If you are invited to a home, you will receive pop-up notification in the APP. You can choose decline or accept. You will also receive notification in the



# **NO.3.2** Voice Assistant





- 1. Click the mic icon in the top right corner and enter the voice assistant page.
- 2. If you do not know how to use it, you can click "?" on the bottom left and check for instruction.



## **NO.3.2** Voice Assistant





3. You can give command to the voice assistant according to the instruction. When giving instruction, please press the mic icon.
4. If you want to do this in a more convenient way, you can click "Add to Home Screen" and create shortcut in the phone home page.



## **NO.3.2** Voice Assistant

6:23 ◀ ◀ TuyaSmart	🗢 🔲	6:23 ◀ TuyaSmart	🗢 🗖	6:23		🗢 💷									
data:	Ċ	Voice Assistant data:text/html;base64,PCFET	Options >		•	$\star$									
<ul> <li>Step 1: Click the button at the born of the screen <sup>↑</sup></li> <li>Step 2: Choose "Add to Home</li> </ul>	bottom	AirDrop Messages Mail	Reminders	Files Fir	nd My Shortcuts	iTunes Store									
Screen T		Сору	ß		0,										
		Add to Reading List	00	TuyaSmart Voice	Assistant										
		Add Bookmark	Ш												
		Add to Favorites	公												
		Find on Page	Q												
											Add to Home Screen	ŧ			
		Markup	$\odot$												
		Print	ē												
< > <u></u>	) (	Edit Actions				<b>,</b>									



5. You can create Voice Assistant shortcut to the phone home page according to the instructions. (The pictures shown in the left are instructions for iOS user. If you are an android phone user, you only need to enable the access to create shortcut in the home page. )



#### **Environment Information** NO.3.3

10:53		🗢 🗩 ,	11:30 🕫		🗢 🛃	11:30 ·	9	🕈 🛃
		ው 👴	Tuya 🗸		ው 🕂	<		
			$\bigcirc$ (	Overcast			$\bigcirc$	
			10 °C Outdoor Temperatu	re Outdoor PM2.5	Excellent Outdoor Air Quality		Overcast	
	$\left[+\right]$		All Devices	Living Room Mas	ster Bedroo 🚥		Hangzhou Wuchanggang Ro	ad >
	No devices, please add					ß	Outdoor Temperature	10°C ~
	Add Device			*		=	Outdoor PM2.5	Excellent
				No devices, please ad	d	ዋ	Outdoor Air Quality	Excellent
				Add Device		٥	Outdoor Humidity	97%
						Jl	Outdoor Wind	4
A Linear	-\Q́-	Ø	<b>^</b>	-\Q́-		-ÿ-	Outdoor UV Index	1
Home	Smart	Ме	Home	Smart	Me			



- 1. After you complete the home information and location, you can see weather and environment information in the home page. You can also click it to see more details. 2. If you have connected sensors devices with the APP(For example:air purifier, thermometer, hygrometer etc), it will show the environment information detected by these devices. 3. You can press the item and drag the information to adjust the orders.(Only home owners and administrators have the access to control this).



# NO.3.4 Add Devices

6:35		···· 🗢 🔳,	11:34 🕫			🗢 💽	6:43 7			<b>?</b>
Tuya Home	•	0 🕂	<	Add Manually	Auto Scan	Ξ	<	Add Manually	Auto Scan	Ξ
- <u>;);</u> ; ;	Sunny	l	Electrician			•	Automa devices w	tically discover Bluet hen the correspondi	ooth/Wi-Fi/Zigbeen ng permission is to	/wired urned on
11.0 °C Outdoor Temperatu	Good G ure Outdoor PM2.5 Ou	ood Itdoor Air Quality	Lighting	Switch (GPRS)	Socket (Wi-Fi)	Socket (Zigbee)	Ensure that the device is ready for hetwork connection.			
All Devices	Living Room Master	Bedroo ···	Large Home Ap	415	41Þ					
			Small Home Ap	Socket (Bluetooth)	Socket (NB)	Socket (other)				
			Kitchen Appliances	Switch (Wi-Fi)	Switch	Switch				
	$\left[ + \right]$		Security & Sensors		(Zigbee)	(Bluetooth)				
	No devices, please add		Exercise & Health	Switch (other)	Power Strip (Wi-Fi)	Power Strip (Zigbee)				
	Add Device		Video Surveillan	12.31	• • • • • • • • • • • • • • • • • • •	<u>e</u> <u>e</u>				
			Gateway and others	Dimming switch	Power Strip (other)	Scenario Switch (Wi-Fi)				
				Scenario Switch (Zigbee)	Scenario Switch (other)	Curtain Switch (Wi-Fi)		Configurin	g Wi-Fi	
Home	-Ò Smart	Me			itch	Wireless Switch				



Click "Add Devices" or "+" in the top right corner to enter add device page. There are two ways of adding devices, which are "Add Manually" and "Auto Scan" . (If you use "Auto Scan" . you need to allow the APP to use Wi-Fi and Bluetooth)

#### tuyal涂鸦智能

## NO.3.4.1 Add Manually- Wi-Fi Devices-Connect to Wi-Fi

11:35 🕫 🗢 🖅	16:10 7
Cancel	Cancel
Select a 2.4GHz Wi-Fi network and enter your password	Select 2.4 GHz Wi-Fi Network and enter password.
If your Wi-Fi is 5GHz, please set it to 2.4GHz first. Common router setting method	If your Wi-Fi is 5GHz, please set it to be 2.4GHz. Common router setting method
<ul> <li> <ul> <li></li></ul></li></ul>	ООООООООООООООООООООООООООООООООООООО
	Which of the following states is your device
Password ©	indicator?
Next	is slowly blinking (2s/time)
	The indicator is not flashing?

 Firstly, you will turn to the page where you need to enter your Wi-Fi password. (Only 2.4G Wi-Fi can be supported.)
 If you already know how to add and reset the device, you can choose the right method according to the status of the indicator. If you are unclear about add and reset device, you can click the "The indicator is not flashing" option to view the guide.





NO.3.4.1

## Add Manually-Wi-Fi Devices

12:07 -	হ 📧,	12:07 🕫	🗢 😥	12:07 🕇		🗢 🐼,	
Cancel	Net Pairing Mode 숙	Cancel	Net Pairing Mode ≒	Cancel	Net Pair	ing Mode <del>年</del>	
Reset	the device	Rese	et · V EZ Mode Default		Reset the device		
0	23		AP Mode			/	TY-US-S10 Smart
Power of	n the device.	Powe	r on the device.		Power on the device.		 Device
Back	Next	Back	Next	Bac	ck Next		



Z7

rt Bulb Light

e Reset Guide

2. After click the "The indicator is not flashing" option, it will jump to the guide page. There are two network configuration modes for devices (except IPC devices and NB devices). They are EZ mode and AP mode. You can switch mode by clicking "Other Mode" in the top right corner. (There is a Guide Video available)



NO.3.4.1 Add Manually- Wi-Fi-EZ Mode





 If you use EZ Mode to connect devices, you need to follow the three steps and set the indicator light to fast blinking.



# **NO.3.4.1** Add Manually - Wi-Fi Devices-Network Configuration

12:20 7	7:20	🗢 🔲	7:29 💼 🗧
Cancel	<	C	Close Report Issue
Adding device Insure that the Wi-Fi signal is god	d. Living Room	Bulb <section-header></section-header>	<section-header><section-header><list-item><list-item><list-item><list-item><list-item></list-item></list-item></list-item></list-item></list-item></section-header></section-header>
Scan Register Init devices. on Cloud. the c	C) alize evice.	Done	Retry Switch Pairing Mode More device pairing FAQs



- 2. If you use EZ mode to
- connect devices, the process is
- presented in the first two
- pictures in the left. You can
- customize the names of the
- devices (64 characters
- maximum) and assign rooms for the devices.
- 3. If it fails to connect the
- device, the APP will show the
- third page in the left. You can
- follow the instructions to solve
- the problems.

#### tuyo<sup>®</sup>涂鸦智能

# NO.3.4.1 Add Manually- Wi-Fi-AP Mode





 If the network in your home is 2.4Ghz and 5Ghz mixed, you can use AP mode (compatibility mode).

2. If you use AP mode to connect devices, you need to follow the three steps in the page to set the indicator light to blinking slowly.



# **NO.3.4.1** Add Manually-Wi-Fi Devices-Network Configuration



3. If you use AP mode to connect the device, you need to connect your phone to a Wi-Fi that starts with the name "SmartLife".





# **NO.3.4.1** Add Manually-Wi-Fi Devices-Network Configuration

12:2 ◀ Tuyas	<b>4</b>	<b>1</b>	2:51 ◀ TuyaSmart		🗢 🔳	<b>2:51</b> ◀ TuyaSmart		· · · · · <b>(</b> )	4
			Settings	Wi-Fi		Settings	Wi-Fi		а
Se	ettings					Wi-Fi			
10	a summer		Wi-Fi			✓ SmartLife- Unsecured Net	-BEEC	<b>∻</b> (i)	
1	Apple ID, iCloud, iTunes & App Store	>	🗸 Tuya-Test		🔒 🗢 🚺				
						MY NETWORKS			5
┝≻	Airplane Mode		MY NETWORKS			Support		ê ╤ (i)	r
<b>?</b>	Wi-Fi	>	SmartLife-BEI	=C		Tuya-Mob	ile	₽ ╤ (j)	
*	Bluetooth O	n >	Support		🔒 🗢 i	Tuya-Test		🔒 🗢 🚺	C
(( <sup>†</sup> ))	Cellular No SIN	/ >	Tuya-Mobile		🔒 🤶 🚺	陆的iPhon	e X	<b>11</b> 4G 🔳 '	S
			陆的 iPhone X		<b>utl</b> 4G 🔳,				n
	Notifications	>	OTHER NETWORKS			Charles E	кs С		
<b>(</b> ((	Sounds & Haptics	>	Charles-5G		A 🗟 🕕	Chanes-5	6	• • 1	D
	Do Not Disturb	>			- · •	ESP_94FF	7D	<b>∻</b> (i)	
			H3C_C156AD_	_5G	🔒 ᅙ (i)	H3C_C156	AD_5G	a 🗟 i	
	Screen Time		MERCURY_5G	_0620	🔒 훅 🚺	MERCURY	′_5G_0620	🔒 🤶 🚺	
$\bigotimes$	General	>	OpenWrt5		₽ <del>?</del> (i)	OpenWrt5	;	₽ ╤ (ì)	
	Control Center	>	TPGuest_D9A	В	<del>?</del> (j)	TPGuest_[	D9AB	<b>?</b> (i)	
AA	Display & Brightness	>	Tuya-Guest		<b>?</b> (i)	Tuya-Gues	st		



. Open the Wi-Fi set up page in the phone nd find hotspots that starts with "SmartLife", click it to connect.

After successfully connecting to the Wi-Fi, eturn the the APP and start the network onfiguration. (The Wi-Fi needs to be 2.4G.
Some names of device's hotspots may not neccessarily start with "SmartLife". It could be customized names.)

#### tuya。涂鸦智能

# NO.3.4.1 Add Manually-Wi-Fi Devices-Network Configuration

12:20 -? 🚮 7:20 ? **–** 7:29 ... 穼 🔳 Cancel < Close Report Issue **Device not responding** Adding device... RGBWC Bulb 🖉 Check demerit points and retry Device added successfully Ensure that the Wi-Fi signal is good. Secon...edroom Maste...droom ① Check if the device has been reset and the indicator is Dining Roon Kitchen Study Room blinking quickly. ② Check if it is 2.4 GHz Wi-Fi. ③ Verify the Wi-Fi password. Q Retry Switch Pairing Mode 0 Scan Initialize devices. More device pairing FAQs Done

6. Connect to the device's hotspot and return to the network configuration page in the APP to continue the process. The page will be shown as the left pictures. After the devices are successfully connected, you can customize the devices' names(64 characters maximum) and assign rooms for the devices. 7. If it fails to connect the device, the APP will show the third page in the left. You can follow the instructions to solve the problems.



#### tuyaầ涂鸦智能

# NO.3.4.1 Add Manually-Wi-fi bluetooth dual mode network

10:39	all Ş	<b>I</b> 9:12 <del>-</del>	÷ ۱۱۱ ک	∎) <b>19</b> :1	14 🕫	al 🗢 🕞
Tuya 🗸	Û	Cancel		Canc	el	
A8 °F Outdoor Temperature Poor Outdoor PM	A2.5 Poor Outdoor Air Quality	Blu The minu oper	search process may take up to two utes. Please do not perform any rations during this time.	S	Select Device to Add	Add
All Devices 餐厅 客厅 Smart Tr Tr Devices to b	插座 测试-vdevo					
双模插座 bk7231s Do not add Home Sma	通… raw测试 Go to add art Me		Scanning nearby devices			



1. When you use the WiFi and bluetooth membrane dual distribution network product, you can connect the device to the power supply first, and the App home page will automatically pop up the device to be connected. If there are multiple devices to be connected, choose the device you need.

#### tuyal涂鸦智能

# NO.3.4.1 Add Manually-Wi-fi bluetooth dual mode network

8:12 -	<b>२</b> ■) 12:20 <b>1</b>	🗢 📷	7:20 🗢 🗩
Cancel	Cancel		<
Enter Wi-Fi Passwo	Addin Ensure that the	<b>ng device</b> e Wi-Fi signal is good.	RGBWC Bulb   Device added successfully     Living Room     Mastedroom     Seconedroom
Line Colure Win Singetworks		Q	Dining Room Kitchen Study Room
are supported		3%	
Support			
Confirm	Scan devices.	Register Initialize on Cloud. the device.	Done



# 2. Connect to the WiFi at home andwait for the device to connect tocomplete the connection.



# NO.3.4.1 Add Manually-Wi-fi bluetooth dual mode network





 Of course, if you are not willing to use bluetooth connection, you can also choose WiFi connection.
 First you can select the corresponding device type. To set the indicator light to the flash state, please follow the three steps in the figure to complete the setting.



## NO.3.4.1

# Add Manually-Wi-fi bluetooth dual mode network

12:17 🕫		🗢 🚺	15:38 <del>1</del>		''' 🔊 🔲	15:39 🛛	ul S 🔳
Cancel	Net Pair	ing Mode ≒	Cancel			Cancel	
	Reset the device			Adding device		Added.	Click to rename
Confirm	1 2 3 that the indicator blinks	slowly.	Ensure th	at the device is power	red on.	CGHN Device ad Living Room Second Bedroom Kitchen S	Added successfully Master Bedroom Dining Room tudy Room
В	confirm indicator slowly b cack Next	link	Scan devices.	Register on Cloud.	C Initialize the device.		Done



# 2. After completing the three steps, wait for the device to connect. After successful connection, the device can be renamed and room classification.

#### <mark>tuyo</mark> 涂鸦智能

# NO.3.4.1 Add Manually-Wi-fi bluetooth dual mode network





 You can also connect the device via bluetooth by clicking the "add device" button in the center of the device list page or clicking the "+" button at the top right.

2. You can enter the "add

device" page, select the device

you want to add and power the

bulb, and reset the device

according to the tutorial.



# NO.3.4.1 Add Manually-Wi-fi bluetooth dual mode network

15:37 🛪	4G 🔲,	19:14 🛛	.ul ≎ 🕞	15:37 🕫	uli 4G 🗩	15:37 🕫	<b>11</b> 4G 🔳
Cancel		Cancel		Cancel		Cancel	
<b>Bluetooth Search</b> The search process may take up to tw minutes. Please do not perform any operations during this time.	wo	Select Device to Add	Add	Adding Bluetooth device.		1/1 has been processed	
						RGBW Bulb 2	2
Scanning nearby devices						Done	



# 3. Wait for the system to search the device and connect the device, and click "complete" after the step.

#### tuyo<sup>®</sup>涂鸦智能

# NO.3.4.1 Add Manually- Wi-Fi-AP Mode





 If the network in your home is 2.4Ghz and 5Ghz mixed, you can use AP mode (compatibility mode).

2. If you use AP mode to connect devices, you need to follow the three steps in the page to set the indicator light to blinking slowly.



## **NO.3.4.2** Add Manually--ZigBee Devices





1. You will have to connect gateway first before connecting ZigBee devices. Therefore, please click "Add Manually >> Others" and choose a gateway. 2、Power on the gateway and connect it to the router through. 3. Please make sure the phone and the gateway connects to the same LAN. (The Wi-Fi needs to be 2.4G.)


# NO.3.4.2 Add Manually--ZigBee Devices

6:04 💼 🕈 🗐	12:20 7	? 😥	6:08 ? •
Connect Device	Cancel		Cancel
Select Device to Add	Addir Ensure that the	<b>ng device</b> e Wi-Fi signal is good.	Smart Gateway (TYGWZ 🖉 Device added successfully
Smart Gateway     Devices Can Be Connected     Bind			Living Room (Mastedroom) (Secondroom)
		Q	
		3%	
		578	
	0	C	
	Scan devices.	Register Initialize on Cloud. the device.	Done



# 4. After successfully adding the gateway as instructed, you can then start to connect the relevant ZigBee devices.



#### **NO.3.4.2 Add Manually--ZigBee Devices**





5. After adding the gateway, you can turn to the gateway page and click "Add Devices" .You will see other devices that have already connected to this gateway. You can also add them to your account.
6. In the latest APP version, it has "Search devices" function so that you can add more devices to your gateway at the same time.



#### **NO.3.4.3** Add Manually--IPC Devices—Wired Network Configuration

2:36 🔊			🗢 🔲	2:35 1	🕈 🔳	2:35 1	📚 🔳
<	Add Manually	Auto Scan	는	Cancel	Net Pairing Mode <del>年</del>	Cancel	Net Pairing Mode <del>年</del>
Electrician	Vi	deo Surveillance		Reset the devic	ce first.	Reset the de	V QR Code
Lighting	•		000	Power the device on and indicator is flashing quic	d make sure the kly or a prompt	Power the device or indicator is flashing	AP Mode
Large Home Ap	Smart Camera	Smart Doorbell	Floodlight Camera	tone is heard		tone is heard	EZ Mode Default
Small Home Ap		NVR	DVR				Cable
Kitchen Appliances	Base Station	NVR	DVR	• @			
Security & Sensors		Access Control		Resetting Do	evices >	Resetting	g Devices >
Exercise & Health	Access Control						
Video Surveillan							
Gateway and others							
				next st	ер	nex	t step



 Most devices can connect with the APP through Smart Mode (the default mode) and AP Mode.
 Except these two pairing modes, some devices (such as IPC devices and gateways) also have Wired
 Network Configuration mode.



# NO.3.4.3 Add Manually--IPC Devices—Wired Network Configuration





2. If you use the QR code to configure the network, you need to set the indicator light of the IPC device to a fast flashing state or hear a prompt tone.

3. The reset steps can be viewed by clickingthe "Perform net pairing as prompted"button.



# NO.3.4.3 Add Manually--IPC Devices—QR Code Distribution Network





4. After clicking "Next" you will be taken to the page for entering the Wi-Fi password.
5. Follow the prompts on the page, please scan the QR code from 15to 20cm away.
6. If you heard a prompt, please click "I heard a prompt" to the next stage.
7. If the network configuration fails, the following page will be displayed.



# **NO.3.4.4** Search Device

8	3:01 7		<b>?</b> •	8:05			🗢 🗩
<	Add Manually	Auto Scan	8	<	Add Manually	Auto Scan	Э
C	Automatically discover Bluet devices when the correspondi	ooth/Wi-Fi/Zigb ng permission is	ee/wired s turned on				e/wired turned on
	Ensure that the device is connect	s ready for ne	etwork >	Ensu	ure that the device connec	is ready for ne	twork >
				1. au th	Search timed out. N Please confirm that t utomatic recognition ne Paring mode.	lo devices fou he device supp and the device	nd. orts is in
				2. re	If the device cannot etrying, please try "M	be found after anual Mode".	
	Configurin	g Wi-Fi			Add Ma	nually	
					Try aç	gain	
					More d	letail	

1. You can search the following devices through Auto Scan, which include Wi-Fi devices, bluetooth gateway devices, bluetooth Mesh devices, Zigbee gateway devices and other Zigbee devices that have connected to your gateway. You can add all these devices in one click.

devices are found, please follow the instructions to solve the problems. Or you can choose to add them manually.



- 2. If the search times out and no



#### **NO.3.4.4** Search Device—Request for Permission

8:0	)1		, , , , , , , , , , , , , , , , , , ,
<	Add Manually	Auto Scan	Э
F	Enable permi scanning o	issions for devices	vices.
11	f you are unsure of the dev all these per	ice type, please emissions	nable
	Enable	Wi-Fi	
	Enable Blu	letooth	
	Start sca	inning	

3. When using "Auto Scan", you need to enable Wi-Fi and Bluetooth of the phone. If you do not enable Wi-Fi, Wi-Fi device will not be searched; If you do not enable Bluetooth, Bluetooth devices that nearby your phone will not be searched.





#### **NO.3.4.4** Search Device—Request for Permission

10:39		ul 🍣 🗊
Tuya 🗸		0 🕀
- Sun	ny	
48 °F Outdoor Temperature	Poor Outdoor PM2.5	Poor Outdoor Air Quality
✔ 发广告	•	日落
All Devices 餐厅	客厅 插座	
		1
	测试	-vdevo ~
Devic	es to be add	ded: 3
415		415
双模插座	bk7231s通	raw测试
Do not add		Go to add
Home	Smart	Me

4. The app is now enabled to automatically scan nearby Bluetooth devices, which improves its functionality with Bluetooth devices.
5. Open the App and go to "Home". The app will automatically search for Bluetooth devices that are in pairing mode. After the devices are found, they will be shown in the home page (like the photo on the left).
6. You can click "Do not add" or "Go to add" to choose whether to add these Bluetooth devices or not. (When searching for Bluetooth devices, Bluetooth permission from the app is required and the devices need to be in pairing mode)





# **NO.3.4.4** Search Device—EZ mode that Supports Add Devices Manually

8:01 🕇			<b>?</b> 🔳 ,	8:12 7	···· 🗢 🔳,	8:11 <b>-</b>			···· <b>?</b> •··	7:20	···· <b>? (</b> )
<	Add Manually	Auto Scan	Ξ	Cancel		<	Add Manually	Auto Scan	Э	<	
Auton devices Ensur	natically discover Blue when the correspond re that the device connect	tooth/Wi-Fi/Zigbe ing permission is <b>is ready for ne</b> tion.	ee/wired turned on twork	Enter Wi-Fi Pa	ssword		Available devi	ces found		Living Room	BWC Bulb vice added successfully
				 2.4GHz 50 ✓	Энz ×		RGBWC	Bulb		( Dining Roon	n Kitchen Study Room
				Only 2.4 GHz Wi-Fi networ are supported	'ks ,						
				🔶 Support	<i>←</i>						
				Password	$\odot$						
	Configurir	ng Wi-Fi		Confirm			Nex	t			Done



7. You can also set NB-IoT Wi-Fi products to quickly flash and use Auto Scan to connect them in one click. (Please use 2.4G Wi-Fi. Also Wi-Fi name and password needs to be entered in the APP.)





# **NO.3.4.5** Scan to Pair Devices : Scan QR code in NB Products or Enter Code

2:58 🗸			···· <b>? II</b> ),	11:04 🕫	<b></b> 🗢 II.
<	Add Manually	Auto Scan	8	Cancel	
Electrician				Add Device	ce or its
Lighting	Temperature and Humidity Sensor (Bluetooth)			packaging and scan it to add the	device
Large Home Ap	Vid	leo Surveillance			
Small Home Ap	Smart Camera				
Kitchen Appliances		Smart Lock —			
Security & Sensors		-			
Exercise & Health	Lock (Wi-Fi)	Lock (Zigbee)	Lock (Bluetooth)		
Video Surveillan	-	0			
Gateway and others	Lock (NB)	Residential Lock PRO			
		Safe Box			
				Scan	
	Safe Box(Wi-Fi)	Safe Box (Bluetooth)		Enter device c	ode
	_	Sensor			_

Choose the NB products you want to connect and click the scan icon on the top upper right corner to scan the device's QR code. Or you can directly enter the IMEI number on the device's label and choose "Confirm" to connect the devices with the APP.(The APP will need phone camera access when scanning.)



#### tuyaầ涂鸦智能

# **NO.3.4.5** Added the distribution method of scanning code distribution network

11:04 I I I I I I I I I I I I I I I I I I I	•
Cancel	
<b>Add Device</b> Looking for the code on the device or its packaging and scan it to add the device	
Scan	

According to the demand, the IoT platform-product management can be added to the scan code distribution network. Just scan the QR code on the product or the outer packaging of the product to jump directly to the distribution page.



#### tuyaầ涂鸦智能

#### **NO.3.4.6** Android Permissions Open Guide

ள் III 15:21 ஞ் ஞ்	NG& 45.2 🔶 🧐	<sup>ሬ</sup> ሰ 🖽 15:21	NOQ 55.7 🔶 1990	tin 🖿 15:21 @ @	NOB 56.7 🔶 199	<sup>46</sup> iu 💷 15:2	21 6 6	NO	Ş.
8	0 🕂	<		<		< (S	amsung	g) How do I t	ur
Security Car	mera-vdevo	Au You can turn on a Settings - Per	r <b>tostart</b> pp automatic startup via missions - Autostart	Please see the for turn on your batter	ery Usage ollowing instruction and ry usage according to your	1. Enter th "Lock Scre "Show Alw	ne mobile een"-oper vays"	e phone setting n the "Always (	js Dn
				pho S	one brand. Samsung <u>Huawei</u>	Settings Connections Connectio	Q 😧	Technological and type (1999) In a second s	S P
Notifica This device is a secur notifications. To ensu notifications, please o if you have turned on	ation Test ity device with alarm re you receive the slick "Test" to check the correpsonding				<u>OPPO</u> <u>Vivo</u> <u>Xiaomi</u>	Wildpaper     Wildpaper     Constraints from Anterna      Constraints from Anterna     Constraints from Anterna     Constraints from Anterna     Constraints from Anterna     Constraints     Const     Constraints     Constraints     C	Ac Screen walpaper In Display, and Clock In Display, and Clock Inter, Find My Mobile K	In the type of a sharp of the clock on the Luck wave in the clock wave in the Luck wave in the clock w	S S B B B B B B B B B B B B B B B B B B
permission. Don't show this m Cancel	essage again Test					2. Go back scroll dow open "Not Display"	k to the " vn to find ification'	Lock Screen" s I the "Notificat '-open "Show o	set ior
			Next		Done	LISPLAY Cock Screen Screen lock type Screen lock type Screen lock type Screen lock type Screen lock type Screen lock type Screen lock type Clock stype Clock stype Screen lock Screen lock	C. 4.4 11 Q. 4.4 R. C. 10 R. 10 R	Lock screen C Lock screen Lock screen C Lock screen Lock screen C Lock screen Lock Scree	
Home S	Ċ- Of Me					Some information such as your pl address on the Lock screen.	fore number or email Ag	ngerprints splock III O <	J



#### 739 🛜 99

#### rn on notifica...

page: Click Display"-click

		5.14		
ays On D	isplay			
			•	
dock and r n't in use.	otifications	when you	μ	
ap to show	W to show for 1	) seconds		
now alwa	<b>ys</b> usły.			
NOW BS SC	theduled			
tyle				
nusic info its of the mu its music co	rmation sic when the ntroller is in u		•	
screen to				
ightness			•	
III	0	<		

tting page and ns" option-Always On

×		48		
tifications				
		1	•	
	2			
I how notifications a creen.	re show	n on the	,	
ityle Y				
content floation content is the a	otification		ກ	
cations to show				l
on Always On Dis	play		•	
III 0		<		

Android mobile phones will trigger push reach detection when security devices are added. If a pop-up window is displayed, click "Detect" and then click "Next" to check the corresponding detection tutorial against your mobile phone model to complete the relevant push reach detection.



# **NO.3.5** Device/Room List



Dev
dev
Clic
cho
or g
"E
mai
can
Ma
Ma



vice Page: You can see all the vices, room names in this page. ck "…" in the right, you can bose to see devices in list view gird view; You can click Equipment management" to mage the devices order; You h edit rooms through "Room magement".



# **NO.3.5.1** Device management

11:04 🗸		<b>''' 🖢</b> ,	11:12 <del>7</del>	
	3 Selected	Done	Device Management	Done
* <b>四色灯 1</b> 客厅	✓ ①		<b>四色灯 1</b> 客厅	
2-vdevo	0		(1) 插座	
客厅			<b>2-vdevo</b> 客厅	
	Remove Device		Remove Device	

To change the sequence of devices,
 click "…" on Home page, then click
 "Device Sequence". Now you can
 drag "≡" to adjust the order of your
 devices. Multi-select devices can be
 batch deleted device management.





#### NO.3.5.1 Room Sequence





2. To manage your rooms, click "…" on Home page, and choose "Room Management", then click the icon appears on the topright corner of the screen. Now you can drag "≡" to adjust the order of your rooms and click "-" to delete the room.



# **NO.3.5.2** Device/Room List

3:15	🗢 🔲,
Tuya Home 🗸	0 🕂
ک Cloudy	,
18.0 °C Good Outdoor Temperature Outdoo	r PM2.5 Outdoor Air Quality
All Devices Living Roo	m Master Bedroo •••
	Offline
Thermal alarm-vd	Thermometer-vdevo
U U	٢
Smart Bulb	Air Conditioning
L	
Heating	Humidifier
PM <sub>25</sub> 16	Offline
All Cleaner	RGBWC Bulb
Home Sma	)- O art Me

3. Device Online/Offline: the module is dark if the device is offline, and bright if the device is online;

4. Some devices will have important data information shown on the Home page. For example, the devices with temperature, like air conditioning, water heater, heating, etc. When the device is open, the temperature data will be directly shown on the device icon with no need to click on it.





#### **NO.3.5.3** Quick Actions for Common Functions





 In Grid View, click the small arrow on the bottom right corner of the device icon to open more common functions, like the switch bottom and temperature adjustment for air conditioning.



#### **NO.3.5.3** Quick Actions for Common Functions

4:26	···· 🗢 🔳)	4:14	🗢 🔳	4:14	? (
Tuya Home 🗸	U 🕂	Tuya Home 🗸	0 🕂	Tuya Home 🗸	Ū (
Overcast			y od Good		y od Good
16.0 °C Good Outdoor Temperature Outdoor PM2.5	Good Outdoor Air Quality	Outdoor Temperature Outdo	oor PM2.5 Outdoor Air Quality	Outdoor Temperature Outd	door PM2.5 Outdoor Air Qualit
All Devices Living Room Mas	ter Bedroo 😶	All Devices Living Ro	om Master Bedroo •••	All Devices Living Ro	oom Master Bedroo
- Thermal alarm vidavia		J°c		(B.c)	
8 mermar alarm-vdevo		Thermal alarm-vd		Thermal alarm-vd	
Thermometer-vdevo	Offline	() ()	6	(J)	(b)
Smart Bulb	(U)	quickop_dp_eco	quickop_dp_temp_set_f	quickop_dp_eco	quickop_dp_temp_se
Air Conditioning Common Functions ~	0	quickop_	dp_eco_off	30°F	) +
Home Smart	<mark>ос</mark> Ме	Home St	mart Me	Home	Smart Me



2. In List View, click "Common
Functions" on the bottom of
device icon to open more device
functions, like the switch bottom
and temperature adjustment for
air conditioning.



#### **NO.3.5.3** Quick Actions for Common Functions





3. When there are more than two "Smart Cameras" in the list, the option of "All Cameras" will appear on the homepage. After you click to enter, you can view the video multiple cameras in one screen.



# NO.4 Device Control

4:14	····· 🗢 🔲
Tuya Home 🗸	0 🕂
Cloud	у
18.0 °C Goo Outdoor Temperature Outdo	od Good por PM2.5 Outdoor Air Quality
All Devices Living Ro	om Master Bedroo ····
J°c	Offline
Thermal alarm-vd	Thermometer-vdevo
U U	U
Smart Bulb	Air Conditioning
L	6
Heating	Humidifier
	Offline
Air Cleaner	RGBWC Bulb
Home S	OOmartMe

1. A device icon will appear in "All Devices" when the device completes pairing successfully. Now you can click on the icon to enter he control panel of this smart device. (The control panel will vary fron device to device)

2. When the device is offline, the icon will show "Offline" and the device is unable to operate.



#### tuyaầ涂鸦智能

# **NO.4.1 Device Control-Individual Control**

4:37 4:38 -2 < 1 < Smart Bulb Smart Bulb \_\_\_\_\_ Scene White The second (1)Left time Schedule Left time Schedule

3. Click the device icon to enter the control panel. Take the light as an example. When the light is off, you can only set "Schedule" and "Timer"; when the light is on, you can set "Scene, Color, Brightness and Schedule". Click
" ?" in the upper right corner of the control panel to manage this device separately.



#### tuyo<sup>®</sup>涂鸦智能

#### **NO.4.1** Device Control-Device Management



Please see the device editing page, as shown in the image:1. Click the icon: you can edit the icon, name and location;2. Device Information: you can view the device's ID, IP address, MAC address, time zone, and online status, etc.;

3. Tap-to-Run and Automation: you can turn on/off or edit the recommended Automoation setting;
4. Share Device: you can share devices with others by entering an phone number/email (Notes: the phone number/email must have registered for TuyaSmart);

 5. Create Group: after entering the page, all devices with the same type as this device that have been added under this account will be automatically displayed. By creating group for them, you can easily manage the devices with the same type (Built-in firmwares must have the same version);
 6. FAQ & Feedback: you can view the FAQ of this device to get help, and also give feedback if you have any problems;
 7. Add to Home Screen: you can enter the control panel of the device directly through your Home Screen;
 8. Check for Firmware Upgrade: you can check latest version here;
 9. Remove Devcie: you can remove the device from device list, and the corresponding "Automation" and "Tap-to-Run" will be removed too;
 10. Restore Factory Defaults: the device will be removed from device list, and all data of the device will be erased.





#### **NO.4.1** Device Control-Device Sharing

4:48 7	•	?■ 4:4	48		···· 🗲 🔳 )	4:48	হ	,
Done	Device Sharing	<		Add Sharing	Done	Done	Device Sharing	
If a permanent recommend tha member and sh Run" Scene wit	resident in your home has an account at you set the account as a family mare all your family devices and "Tap h the family member.Home Settings	Regi p-To- s	ion C	China +86 Mobile Phone/Email	>	If a permanent recommend th member and sl Run" Scene wi	resident in your home has an account at you set the account as a family hare all your family devices and "Tap-" th the family member.Home Settings	t, we To-
		Acc	ount			The device has	s been independently shared to the fo	llo
							De	elete
Device is	not shared, add an account to share in	t						
	Add Sharing						Add Sharing	



1. Click "Device Sharing" on the "Device Management" page to enter the device sharing page. 2. After entering the "Device Sharing" page, click "Add Sharing" at the bottom of the page, and enter the account. (People you share with should also have a TuyaSmart account, and in the same region as you; accounts in different regions do not support device sharing.)

3. If you do not want to continue sharing, you can delete the shared account by long press in Andriod system, and by swiping left in Apple system.



# **NO.4.2** Device Control-Group Control

5:04	🗢 🔲	5:04		···· <b>(;</b>	5:07	🗢 🗖
<		Cance	Select Device	Confirm	Smart Bul	b Group 🗾 🖊
	<i>a</i> .	Devices ur	nder same group can be controlled	simultaneously		
Smart Bulb	<u>/</u> >		Smart Bulb	0		
Device Information	>	0	Tuya Home		devices	
Tap-to-Run and Automation	>					
Others					$\bullet$	
Share Device	>					
Create Group	>					
FAQ & Feedback	>					
Add to Home Screen	>					
Check for Firmware Upgrade	>				Timer	

#### **Remove Device**

**Restore Factory Defaults** 



- Click "Create Group" on the device editing page.
- The page will show the devices with the same type that can be created into one group. After selecting the devices, click

"Confirm", then enter the group name, and click "Save" to complete.

3. After the group is successfully created, it will automatically jump to the group control panel. You can now control these devices in a group.



# **NO.4.2** Device Control-Group Control



图2



4. The group will be shown in "All Devices" after being created, and you can easily control it thourgh Home page;
5. After entering the group control panel, you can click

" " in the upper right corner to edit the group information, and to delete this group by clicking "Dismiss Group" .



#### **Smart-Automation NO.5**

7:28	📚 🔳)	7:28		🗢 🔲
Tuya Home 🗸	0 🕂	Cancel	Smart Settings	Save
Tap-to-Run Automation		Conditi	on	
		Any Condi	tion Is Met ~ Add Condition	
Execute automatically according t as the weather, device state	to conditions such us, and time.	Task		•
Add "Automatic	ун 		Add Task	
Recommend		Name Enter the	name	>
<b>深夜,淡黄灯光呵护睡眠</b> 1 Device(s)	+	Style		•>
		Effective	Period	All-day >
Home Smart	O Me			



1. Under "Automation" in the "Smart" page, click "Add Automation" or "+" on the upper right corner to enter the "Smart Settings" page. 2. By clicking "Add Condition". you can add multiple conditions (you can not add other conditions with "Click to execute"), and multiple tasks (you can also select a "Tap-To-Run"). Then, you can edit the name of this automation and set a effective period for it.



7	:06		···· 🗢 🔲)	7:07		···· 🗢 🔲	7:06		<b>?</b> 🔳
<		Create Smar	rt	<	Weather change		<	Temperature	Next
S	Set co	nditions	Set up tasks	Temperature		>	Current City		杭州 >
	\$	Click to execute	>	Weather		>	<	=	>
	۲	Weather change	>	PM2.5		>		<ul> <li>✓ 32°C ►</li> </ul>	
	•	Position change	>	Air Quality Sunset/Sunris	e	>	-40°C		40°C
	٩	Schedule	>	Wind Speed		>			
	*	Device status chang	ge >						



 After adding "Automation", you will see a page called "Create Smart" that will guide you through the setting.
 You need to set up conditions that will be used later to trigger the scenario. Here, we take "Weather change" setting as an example.
 After you click" Weather change",

you need to set up conditions in more specific terms. Here we choose

"Temperature" as an example.4. After you choose the temperature you want, click "Next" to save the setting and go to the next step.



7:07		···· 🗢 🔳)	7:07			🗢 🔳	7:08		🗢 🔲
<	Create Smart		<	All Devices	Living Room	Ма	<	Select Function	Next
			U	Group		>			/
Set Temp	conditions Set up	p tasks	U	Smart Bulb ( Group	Group	>	开关	/	on >
			_				Set Temp		26°C >
	Execution equipment	>	6 e	智能门锁-vd	evo	>	Mode		Cold >
۲	Executive intelligence	$\rightarrow$		smart strip		>	风速		high >
	Send notification reminder		ų	Smart Bulb		>	自动模式		>
			(J.c	Thermal alar	m-vdevo	>	ECO模式		>
2	Delay	>		Air Conditior	ning	>	干燥模式		>
							换气模式		>
			L	Heating		>	Anion		>
				Humidifier		>	Auxiliary Heat		>
			1	Air Cleaner		>	Light		>
							童锁		>



5. After the conditions are set, the app will turn to page for setting up tasks.
6. Here we choose "Execution
Equipment" as an example, which means choosing an equipment for executing the tasks.

7. Here we choose the air conditioning as an exmaple.

8. After choosing the device, you can set up multiple "functions" for it. For instance, we choose "Switch: On, Set Temp: 26°C, Mode: Cold, Wind: High", which means that when the conditions we set are met, these functions will be on. Then click "Next" to save and go to the next step.



7:06		<b>?</b>	7:07		🗢 🗩	17:57 <del>1</del>	ul 🗢 🔳
<	Create Smart		<	Weather change		< Su	unset/Sunrise Next
Set or			Temperature		>	Current City	杭州 >
561 00		0K5	Humidity		>	Sunrise	
	Click to execute	>	Weather		>	Sunset	
۲	Weather change	>	PM2.5		>		
•	Position change	>	Air Quality Sunset/Sunris	se	>		
٢	Schedule	>	Wind Speed		>		OFFSET
٠	Device status change	>				15 minu 10 minu	utes before sunrise utes before sunrise
						5 minut	tes before sunrise
						5 min	Sunrise utes after sunrise
						Cancel	Save
						_	



After adding "Automation", you will see
 a page called "Create Smart" that will
 guide you through the setting.

2. You need to set up conditions that will be used later to trigger the scenario. Here, we take "Weather change" setting as an example.

 After you click" Weather change", you need to set up conditions in more specific terms. Here we choose

"Sunset/Sunrise" as an example.

4. The execution conditions can be selected from sunrise or sunset, and the time period before and after sunrise or sunset can also be selected. After selecting the execution time and go to the next step.



7:07		···· 🗢 🔳)	7:07			🗢 🔳	7:08		🗢 🔲
<	Create Smart		<	All Devices	Living Room	Ма	<	Select Function	Next
			U	Group		>			/
Set Temp	conditions Set up	p tasks	U	Smart Bulb ( Group	Group	>	开关	/	on >
			_				Set Temp		26°C >
	Execution equipment	>	6 e	智能门锁-vd	evo	>	Mode		Cold >
۲	Executive intelligence	>		smart strip		>	风速		high >
	Send notification reminder		ų	Smart Bulb		>	自动模式		>
			(J.c	Thermal alar	m-vdevo	>	ECO模式		>
2	Delay	>		Air Conditior	ning	>	干燥模式		>
							换气模式		>
			L	Heating		>	Anion		>
				Humidifier		>	Auxiliary Heat		>
			1	Air Cleaner		>	Light		>
							童锁		>



5. After the conditions are set, the app will turn to page for setting up tasks.
6. Here we choose "Execution
Equipment" as an example, which means choosing an equipment for executing the tasks.

7. Here we choose the air conditioning as an exmaple.

8. After choosing the device, you can set up multiple "functions" for it. For instance, we choose "Switch: On, Set Temp: 26°C, Mode: Cold, Wind: High", which means that when the conditions we set are met, these functions will be on. Then click "Next" to save and go to the next step.



#### **Smart-Automation NO.5**



# conditions. nobody is home.



9. Set "Condition" and "Task" to save. 10. Click "+" on the upper right corner to add multiple

11. Select effective period at bottom of the page for your "Automation" . Here, we choose "19:00 - 3:00" to avoid air conditioning being turned on during working hours when



7:18		···· 🗢 🔲,	7:19		🗢 🔳
<	Create Smart		<	Create Smart	
	• • •			Create from templat	e
Set co	onditions Set up	tasks	Automatio	n	
₽	Click to execute	>	日落,亮 1 Device(s)	适黄灯光调配温馨	+
۲	Weather change	>	🛎 ·		ME
0	Position change	>	日出自动 1 Device(s)	D熄灯,节能无处不在	+
٩	Schedule	>			
٠	Device status change	>	消辰,为 2 Device(s		+
	Create from template				

1. App will recommend some "Automation" and "Tap-to-Run" based on your devices, which you can use directly. 2. Click "Create from template" at bottom of the "Create Smart" page to get some recommended "Automoations" .



#### tuyol涂鸦智能

# NO.5.1

#### **Smart-Automation-Add Condition**





 Take "Leave or Arrive" as an example, you can set some certain actions to be triggered when you are leaving or arriving.
 (To use this function, you need to allow the App to access your location. The function is currently unavailable in Android version.)
 Click "Leave or Arrive", and select your location, then click

"Next" to finish setting. This setting will enable you to control your devices and to executive your tasks within 110-1023 meters from your location.



#### NO.5.1 **Smart-Automation-Add Task**

7:28		···· 🗢 🗩 )	7:55		\$ •.
Cancel	Smart Settings	Save	<	Select Task	
Condition		Đ	Launch Tap to	Run	>
			Enable or Disa	able Automation	>
	Add Condition		Send Notifica	tion	>
Task		•	Time to left		>
	Add Task		Device		>
· · · · · · · · · · · · · · · · · · ·					
Name Enter the r	name	>			
Style		•>			
Effective P	eriod	All-day >			



1. Click "Add Task" or "+" on the upper right corner to enter the "Select Task" page.

2. This "Task" can be a device switch under a certain condition or an automation execution.

3. The tasks include: "Launch Tap to Run", "Enable or Disable Automation", "Send notification". "Time to left" and "Device".



# **NO.5.1** Smart-Automation-Effective Period

8:04	🗢 🔳 )	8:04					🔅	•
Cancel Smart Settings	Save	<	1	Effectiv	e Perio	od	N	ext
Condition Any Condition Is Met ~	o	City Please select a region >						on >
Temperature : <16°C	>	Effective P	Period					
杭州		All-day 24 hours						$\bigcirc$
Task	Ð	Daytime From sunris	se to sun	set				0
Group:Smart Bulb Group Switch:ON	>	Night From sunse	et to sum	rise	0.117 0.0			$\bigcirc$
Group:Smart Bulb Group Bright:265	>	AM 12-00-F	-W 11-29	Same Da	Y GMT+0	8.00		
			ам 120	0	Sa	ame Day	РМ О	
Name Enter the name	>		Start	0 -		End	7	
		11	59		10	58	AM	. 1
Style	• >	12	00	AM	11	59	PM	- 1
		1	01	РМ	12	00		
Effective Period	All-day >		Cance	el		OK		
			-			_		

 You can select the effective period to the automation you set.
 For example, if you want to set an automation, where the night light will turn on when the sensor detects any human action, you can select Night for Effective Period so that the automation will be off in the daytime.



#### tuya。涂鸦智能

#### **Smart-Automation-Examples** NO.5.1

8:10		···· <b>? D</b> ,	
Cancel	Smart Settings	Save	
<b>Con</b> Any C	<b>Condition</b> Any Condition Is Met ~		
٥	Temperature : <-40°C 杭州	>	
Task	(	•	
U	Group:Smart Bulb Group Switch:ON	>	
<b>Name</b> Enter	e the name	>	
Style		•>	
Effect	tive Period	All-day >	

The completed automation setting of condition and task is shown in the image. There are mainly 4 types of automation can be achieved:

1、 Linkage among devices: you can set that aroma diffuser and air purifier to be turned on while air conditioning is on;

device: you can set to automaticlly turn on the air conditioning while the temperature is over 29°C;

3. Timer: to automaticlly open the curtain at 8am on every morning;

4. Location: to trigger some actions when someone leaves or arrvies somewhere. For examle, to open the air conditioing and water heater when you are nearby your home.



#### 2. Linakge between environment and
#### tuyaầ涂鸦智能

NO.5.1

#### Smart-Automation-Push messages support multiple selection

18:03	9	<b>''II \$ ■</b> `	18:03 ৵	<b>''II \$ D</b> '
<	Select Notification Method	Next	Cancel Creat new Smart	
Multiple	items selectable		Operativism	
ø	Message Center	0	Any Condition Is Met ~ Schedule:17:00	+ >
હ	Phone Notification	0	Task	Ð
	Message Notification	0	Message Center On	>
			C Phone Notification On	>
			Name If Schedule:17:00 Weekend, Send Notification→Message Center Send Notification→Phone Notifi	>
			Style	•>
			Effective Period	All day $>$
			Save	

1.Click "create a new account", the graffiti will pop up and click "smart - add - send notification reminder" to enter the "select reminder mode" page. This page feature supports multiple selections (at least 1, and at most 3). If the phone notification and SMS reminder are not purchased, you can only choose the message center. 2. After completing the configuration, return to the home page of automation, which can be combined according to the selected push mode.





## NO.5.2 Smart-Scene

8:13 💼 🗘	7:22 💿	7:22	7:22 💼 🗧
Tuya Home 🗸 🛛 🕕 🕂	< Create Smart	< Create Smart	< Executive intelligence
Tap-to-Run Automation ····			Launch Tap to Run
	Set conditions Set up tasks	Click to execute	Enable or Disable Automation
	Click to execute >	+ Execution equipment	
Control multiple devices with one tap or by using an Al speaker through voice commands	🔆 Weather change >	Executive intelligence	
Add "Tap-To-Run"	Position change	Send notification reminder	
	Schedule >	Z Delay >	
	☆ Device status change >		
Home Smart Me			



1. Under "Tap-To-Run" in "Smart" page, click "Add Tap-To-Run" or "+" on the upper right corner to enter the setting page. 2. You must choose "Click to execute" as a condition. 3. You can not add "Luach Tap to Run" or "Send Notification" as a task.



#### NO.5.2 Smart-Scene

7:22		···· <b>?</b> •••	7:22		<b>?</b> •	7:22		🕈 🔳
<	Executive intelligence		< Se	lect "Automation"Scene	Next	Cancel	Creat new Smart	
Launch Ta	ap to Run	0	scene_if ?	杭州 Temperature : =32°C,		Cond	lition	Đ
Enable or	Disable Automation	>	Cloudy M	lode	0	₽.	Click to execute	
			Sunset		0	Task		Đ
						<u></u>	scene_if 杭州 Temperature =32°C, "Air Conditioning ' 关:on Automation:Enable	e: '开 >
						<b>Name</b> Enable Tempe 开关:or	e Automation"scene_if 杭州 rature : =32°C, "Air Conditi า"	oning "
						Style		<b>()</b> >
							Save	



4. When choose "Enable or Disabele Automation" as a task, you need to preset an "Automation" scene. 5. After clicking "Enable or Disabele Automation", the existed automation will be shown on the screen. Select to choose "Enable" or "Disable" it and click "Next" . Last, click "Save" and enter your scenario name to complete setting. ( "Effective Period" is unavailable for "Tap-to-Run")



#### "Automation" supports gateway for Tap to Run of local scenario

New ZigBee gateway supports "Automation" Tap to Run of local scenario, that is if all the tasks of an "Automation" and the device are under new ZigBee gateway, the "Automation" can be executived in offline mode. Even if your network is offline, the devices and tasks bound under new ZigBee gateway will still execute the automation that you have set before.





#### Smart-Scene-Zigbee gateway linkage data backup and recovery NO.5.2

The App now supports the function of "Zigbee gateway linkage data backup and recovery". This means that even if the zigbee gateway in the user's home is removed, the previous linkage scene information will be automatically retained, and the linkage scene information will be restored after the device is reconfigured in the user's home (normal configuration, automatic discovery).



#### tuya。涂鸦智能

# NO.5.3 Smart-Add/Edit/Delete





#### 1. The "Tap-to-Run" and

"Automation" that you have set will be shown on the "Smart" page. By clicking "..." on the upper right corner, you will be able to edit or change the order for them. 2. Click to enter the editing page, and you can change the order or swipe left to delete your scenario or automation. (for Apple system, click

"-" to delete)



# NO.5.3 Smart-Add/Edit/Delete

1:51	🗢 🔲	1:57		<b>?</b> 🗩,	8:21 <b>1</b>	<b>?</b>
Tuya Home 🗸	ው 🕂	Cancel	Edit	Save	Tuya Home 🗸	0 🕈
Tap-to-Run Automatio	on •••	Condition		•	Tap-to-Run Automation	
<ul> <li>•</li> </ul>	-					
Sleeping 1 Device(s)	<b>Playing</b> 2 Device(s)	lick to execute		Delete	◎ ♥	
Cood Night	Working	Task		0		
2 Device(s)	2 Device(s)	Smart E Switch:C	Bulb	>		
87						
Reading 2 Device(s)	Open All 1 Device(s)	Name Sleeping		>		
		Style	C	> <b>**</b>		
		Show on Home	Page			
	Add to Siri		Delete		Edit	
Home Sm	art Me	_			Disable	



3. Click "..." on upper right corner of your "Tap-to-Run" or "Automation" to enter the editing page. 4. Swipe left to delete any "Condition" or "Task". 5. Click "+" to add new "Condition" and "Task". 6. Click "Delete" at bottom of the page to remove the entire "Tap-to-Run" or "Automation". 7. By clicking your "Automation", you can

choose to edit or remove it directly.



#### **NO.5.3** Smart-Add/Edit/Delete





- Click "Add to Siri" on the bottom right corner of the "Smart" page to enter the "Siri Shortcut" page.
- 2. You can add any "Tapto-Run" to Siri
- 3. On the "Add to Siri" page, you can set custom phrase for Siri to trigger your "Tap-to-Run" (This function is only available for iOS system over 12.0 version)



# NO.5.3 Smart-Scene logs





<b>? I</b>	
Monday	
et" 开	
et" 开	

1.Click the log display interface to view the scene log in reverse chronological order.

 Store log information for up to 7 days intelligently.

3. Click a specific log to jump to the corresponding scene editing page.
4. If a device fails to execute during automated execution, an alarm message will be pushed in the notification center and the execution failure log will be kept, through which the specific execution failed device can be viewed.



# NO.5.4 Scenario Execuation in LAN

The new function "Scenario execuation in LAN" has been added. With the LAN, all the tasks of the scenario can be executed without Internet. LAN will control the devices depending on the order of the device actions.





### NO.6 My Home





#### **1. Voice Control**

- 2. Switch/Add Home
- Click to set the weather. You can change the order of the information, and the top 3 will be shown on the home page.
- 4. Add different types of Smart devices
- Click your "Tap-to-Run" to chnage your living scenarios quickly
- 6. Switch your rooms to check your devices in different rooms



15:1	57	::!! ? 🗩
		Ξ
C		>
	Home Management	>
0	Watch	>
$\bigcirc$	Message Center	>
	FAQ & Feedback	>
	More Services	>
0	Settings	>
ŀ	Home Smart	Me

1. Home Management: manage your home and home members;

 Watch: this will be shown only if your iPhone has bound Apple Watch. You can control your devices and execute "Tap-to-Run" by Apple Watch;
 Message Center: it includes three types of messgae, Alarm, Home, and Bulletin, where you can select different Do-Not-Disturb Schedules for them;
 FAQ & Feedback: it includes All Questions, Network Diagnosis, Report Issue, FAQ, and My feedback.
 More Services: it includes Al Filtered Notification, Cloud

Storage for Cameras, Phone Notification, and 8 thrid-party access services.

6. Settings: it includes Sound, App Notification, About,Network Diagnosis, Upload Log, Clear Cache and Log Out(Upload Log is only available in iOS system)





# NO.7.1 "Me" —Watch

15:15 🔊	<b>::!! \$ •</b>	15:15 🕫	::!! ? ■	15:15 🕫	::!! <b>?</b> •	17:36 🕫
	Ξ	< Watch		Cancel	Done	Cancel
	>			<b>Device</b> Home: Tuya Home		Available "Tap-To Home: Tuya Home
Home Management	>			😑 🥛 Smart Bulb		e Sleeping
🗍 Watch	>			e Air Conditioning		Playing
💬 Message Center	>			No devices added		Good Night
💟 🛛 FAQ & Feedback	>			🕂 🥛 Smart Bulb Group		No "Tap-To-Run" Scene add
More Services	>	Device	+	The following devices do not support /	Apple Watch.	+ Working
Settings	>	Available "Tap-To-Run"	+	+ J <sup>*</sup> Thermal alarm-vdevo		+ Reading
				Thermometer-vdevo		🕂 🚺 Open All
				Heating		
Home Smart	Me	Apple Watch Operation Instructio	ons	Humidifier		





1. Click "Watch" on "Me" page to enter the "Watch" operation page. 2. Click "Device" too show all your Smart devices. You can add devices by clicking "+" . Some devices are not supported by Watch. 3. Click "Avaliable Tap-To-Run" too add your "Tap-To-Run" 4. All the notification in "Message Center" will also send to Watch.



# **NO.7.2** "Me" — App Notification Settings

15:15 🕫	::!! \$ •	5:58	<b>?</b> 🔳,	5:58	📚 🔲,
	Ξ	< Settings		Notifications S	Settings
	>	Sound	$\bigcirc$	Enable notifications	
		Push Notification	>	Alarm	Allow
Arrow Management	>	About	>	Do-Not-Disturb Schedule	on >
🗍 Watch	>	Network Diagnosis	>	Home	Allow
💬 Message Center	>	Upload Log	>	Bulletin	Allow
FAQ & Feedback	>				
More Services	>	Clear Cache	9.1/M >		
Settings	>	Log Out			
Home Smart	Me				
			-		



# There are two ways of notification setting: the first, Me - Settings - App Notification



# **NO.7.2** "Me" — App Notification Settings

15:15 <i>7</i>	::!! 🗢 🔲	3:38 1 5:58	<b>? ()</b> ,
	Э	< 🔶 📥 🌒 🛞 < Notifications Settings	)
	>	Home Enable notifications	
Home Management	>	Image: Space of the system       Alarm       Alarm <t< td=""><td>ow ON &gt;</td></t<>	ow ON >
🗍 Watch	>	17 January Home All	ow 🚺
💬 Message Center	>	Bulletin All	ow 🚺
FAQ & Feedback	>	Your "智能网关 (TYGWZ-01) "wifi module update is completed.	
More Services	>	Click here or pull up to load more	
Settings	>		
Home Smart	Me		



# 2. The second, Me - MessageCenter, and then click the gearicon on the upper right corner



# **NO.7.2** "Me" — App Notification Settings

6:30		<b>?</b> 🔲	5:58			<b>?</b>
<	Notifications Settings		<	Notifications Sett	ings	
Enable no	tifications	$\bigcirc$	Enable no	tifications		
			Alarm		Allow	
			Do-Not-D	isturb Schedule		on >
			Home		Allow	
			Bulletin		Allow	
					-	



3. Turn off the notifications to unable any messages,
including Alarm, Home, and
Bulletin, where you can set
them separetly when you
enable notificatinos.



#### NO.7.3 "Me" — Message Center

3:38 🔊				🗢 🗩,
<	<b>.</b>	8	))	$\odot$
Home				≡₹
<b>31</b> Janua	ry			
¢	<b>Firmware</b> Your "蓝牙M module upc	updated. IESH (SIG) late is comp	10 网关"blueto bleted.	:14:59 PM poth
17 Januar	ry			
Ø	<b>Firmware</b> Your "智能网 update is c	<b>updated.</b> 刚关(TYGW ompleted.	3 Z–01) "wifi	:37:25 PM module
(	Click here o	or pull up t	o load mo	re
	_			

1. "Alarm" includes device alarm, automation notification, alarm, fail to do device timing;

2. "Home" includes: adding/removing home members, deleting home, setting one member as administrator, adding devices, sharing devices, etc;

3. "Bulletin" includes feedback from users, offical notification, etc.





#### NO.7.3 "Me" — Message Center

6:44			🗢 🔲	6:44	Ļ					<b> ? ()</b> ,
<	Notifications Sett	ings		Cance	el	Add	sche	dule		Save
Enable no	tifications			Do-No	ot-Distu	urb De	vice			>
Alarm		Allow		Repea	ıt				Eve	eryday >
Do-Not-D	isturb Schedule	٢	Not set >							
Home		Allow			рм 11:0 Start	0		ı	Next Day / 7:00 End	ам )
Bulletin		Allow		10	59	ΔΝΛ		6	59	
				11	00	PM		7	00	AM
				12	01			8	01	PM



4. Message Center enables you to set Do-Not-Disturb in a specific period.

5. Click "Do-Not-Disturb Schedule" to set the period you want. Please select a Do-Not-Disturb device first before you set a time.



#### NO.7.3 "Me" — Message Center





6. Click "<" to complete setting and return to the schedule setting page after selecting the devices.

7. Click "Add schedule" to add more "Do-Not-Disturb Schedule" .

#### tuyo<sup>®</sup>涂鸦智能

### NO.7.4 "Me" —FAQ & Feedback

15:15 🕫	::!! ? 🔲	9:20 💼 🕫
	Ξ	< My feedback
	>	FAQ How to add device in App for Internet connection ? (Wi-Fi)
Home Management	>	Quick Guide of Using Amazon Echo to Control Smart Devices
Watch	<u> </u>	Quick Guide of Using Google Home to Control Smart Devices
	(	What if the third party is connected but the voice control fails?
Message Center	,	How to use the Tmall Genie to control smart devices?
💭 🛛 FAQ & Feedback	>	What if the device is offline?
More Services	>	How do I set my device to network connection status? (Wi-Fi)
Settings	>	Device-connection failure?
		How to share my device for family use?
		How to deal with issues with distribution hetwork after Apple system is upgraded to
Home - Č- Smart	Me	Image: Constraint of the second se

1. Click "Me - FAQ & Feedback" to enter the help center. You can search questions or send any feedback to us here,

2. My feedback: you can check your feedback here.

3. FAQ: you can access frequntly asked questions while using TuyaSmart.

4. All: you can choose any device to see related FAQ, or select "Device networking issues", "APP use issues", amd "Third-party control issues" for corresponding FAQ.

5. Netwok Diagnosis: it helps us to solve your problems faster, and the process may take about 2 minutes.

6. Report Issue: please submit your questions, contact information, and image here if you have any problems while using TuyaSmart.





#### **NO.7.5** "Me" — More Services



 Click "Me - More Services" to find more services includes:

 Al Filtered Notificincluding third-party access service.
 Featured services mainly ation: report any images uploaded by camera; (To get this service, please add Smart camera)
 Cloud Storage for Cameras: after purchasing this service, users can watch history videos uploaded by devices to the server; (To get this service, please add Smart camera; the history video can not be download)
 Phone Notification: to keep your family safty,

(3) Phone Notification: to keep your family safty, you will receive a phone call once the notification conditions has been triggered. (The phone number will be the one you used for registration. If you use an email to register, please set a phone number to receive phone notification.)
2. Third-party Access Service: please click to see how to connect and use.











	×	
ation	1	
nnt. and enter		>

To improve user experience of thrid-party access service, the app is now able to link to thridparty virtual assistant with verification code.



4:11 <del>7</del>		···· 🗢 🔳 )
<	About	
Rate Us		>
About TuyaSmart		>
Privacy Policy		>
User Agreement		>
Open Source Compo	onent License	>
Current Version	3.13.0 (20191	029213138)
©2019 Tuya Ir	nc. All Rights Reserve	d

1. Click "Me - Settings - About" to find more information about this APP. 2. Click "Rate Us" to rate us through App Store. 3. Click "About TuyaSmart" to find more TuyaSmart information through Tuya website. 4.Click "Privacy Policy" to view Tuya Mobile Privay Policy. 5. Click "User Agreement" to view Service Agreement of Tuya Smart Platform. 5.Click "Open Source Component License" to view all the open licenses list. 6. Check current version of this APP.





# NO.8 Personal Center

5:50 7	···· 📚 🔳 )	5:50	···· 🗢 🔳 )
< Personal Cer	iter	< Account	t and Security
Profile Photo	>	Mobile Number	
Nickname	>	Region	China
Account and Security	>	Change Login Passwo	rd >
Temperature Unit	°C >	Gesture Unlock	Unset >
Time Zone	Chongqing >	Deactivate Account	>

Click "Me - Profile" to enter Personal
 Center to edit your photo, nickname,
 temperature unit and time zone here.

2. Click "Account and Security" tochange your password or pattern lock,and to deactivate your account.



#### tuyaầ涂鸦智能

#### **NO.8.1** Account and Security-Account Deactivation

8:03	📚 💽 '	8:03	···· 📚 🗩 )	8:03	<b>?</b> 🗩	
< Account and	Security	Cancel		Cancel		
Mobile Number	86-13513842644	Permanently	<sup>,</sup> disabled on	Permanen	tly disabled on	
Region	China	12/1/2019	00:00:00	12/1/20	019 00:00:00	
Change Login Password	>	If you log in to your acc your deactivation reque will delete all information follows:	count before this date, st will be canceled. We n under your account as	If you log in to your your deactivation re will delete all inform follows:	account before this date, equest will be canceled. We nation under your account as	
Gesture Unlock	$\bigcirc$	<ul> <li>All of your device info</li> <li>All of your message I</li> <li>All of your account in</li> <li>All of your images/vi</li> </ul>	ormation ogs formation deos captured by the	<ul> <li>All of your device</li> <li>All of your messa</li> <li>All of your accou</li> <li>All of your image</li> </ul>	information age logs nt information	
Change Gesture Password	>	<ul> <li>All of your smart device (ga</li> </ul>	ce status information	<ul> <li>All of your smart</li> <li>All of your device</li> </ul>	device status information	
Deactivate Account	>	<ul> <li>All of your device (ga</li> <li>All of your feedback</li> <li>All of your infrared in</li> <li>All of your smart scel</li> <li>All of your auth2.0 in</li> <li>All of your order info</li> <li>All of your payment in</li> <li>All of your coupon in</li> </ul>	information formation ne (linkage) information formation mation nformation formation	<ul> <li>All of your device (gateway) information</li> <li>All of your feedback information</li> <li>All of your infrared information</li> <li>All of your smart scene (linkage) information</li> <li>All of your auth2.0 information</li> <li>All of your order information</li> <li>All of your payment information</li> <li>All of your coupon information</li> </ul>		
				Are you sure y the	ou want to deactivate e account?	
				After the account is d this account will	eactivated, all user data under I be deleted permanently.	
					ОК	
		Cor	nfirm			
					Cancel	



- Click "Me Profile -Account and Security" .
- 2. Click "Deactivate
  Account" at the bottom
  of the page. Once you
  confirmed, your account
  will be permanently
  deleted after 7 days and all
  data will be removed.
- The deactivation will fail if you re-login the account before the process done.



#### **NO.8.2** Personal Center-Pattern Lock

5:50	📚 🗩 )	5:50		🗢 🗩	5:57		<b>?</b> •.
<	Create Gesture Password	<	Create Gesture Passwor	d	<	Enter gesture passwore	d
Create ar operating	<image/> <text><text></text></text>		Enter gesture password			Enter gesture password	



 Click "Pattern Lock" to set a pattern to login.
 Click "Forgot Pattern Lock" if you forgot it. APP will send you a verification code to reset your pattern.



# Thank You

注:

本文配图均为IOS版应用界面, Android 版与此会有细微差异

产品及软件在不断升级中, 文本列出的数据及软件界面仅用于说明, 如有变化恕不另行通知

